

TITLE Défilement bannière
TITREPAGE 1 OF 2
PAGE DE

Défilement d'un texte sur l'afficheur LED 7 segments :

000000.000000.00

Exécuter le programme : [ADDR] 0200 [GO]

0200			* = \$0200	0252	E0 00		CPX #\$00
0200	AE 61 02	BANN	LDX \$0261	0254	D0 FB		BNE \$0251
0203	BD 62 02		LDA \$0262,X	0256	88	DL2	DEY
0206	8D 02 80		STA \$8002	0257	A9 00		LDA #\$00
0209	AE 61 02		LDX \$0261	0259	8D 03 80		STA \$8003
020C	BD 68 02		LDA \$0268,X	025C	C0 00		CPY #\$00
020F	8D 03 80		STA \$8003	025E	D0 F6		BNE \$0256
0212	20 4D 02		JSR \$024D	0260	60		RTS
0215	EE 61 02		INC \$0261	0261	00	IND	.BYTE \$00
0218	AE 61 02		LDX \$0261	0262	9F	RANG	.BYTE \$9F
021B	E0 06		CPX #\$06	0263	AF		.BYTE \$AF
021D	D0 E1		BNE \$0200	0264	B7		.BYTE \$B7
021F	A2 00		LDX #\$00	0265	BB		.BYTE \$BB
0221	8E 61 02		STX \$0261	0266	BD		.BYTE \$BD
0224	CE 7B 02		DEC \$027B	0267	BE		.BYTE \$BE
0227	AD 7B 02		LDA \$027B	0268	8D	LETT	.BYTE \$8D ;C
022A	C9 00		CMP #\$00	0269	85		.BYTE \$85 ;L
022C	D0 D2		BNE \$0200	026A	BD		.BYTE \$BD ;O
022E	A9 FF		LDA #\$FF	026B	23		.BYTE \$23 ;N
0230	8D 7B 02		STA \$027B	026C	8F		.BYTE \$8F ;E
0233	A0 00		LDY #\$00 ; depile	026D	AE		.BYTE \$AE ;S
0235	A2 00		LDX #\$00	026E	40		.BYTE \$40 ;.
0237	B9 68 02		LDA \$0268,Y	026F	1F		.BYTE \$1F ;P
023A	8D 7A 02		STA \$027A	0270	37		.BYTE \$37 ;H
023D	C8		INY	0271	A9		.BYTE \$A9 ;W
023E	B9 68 02	MOVE	LDA \$0268,Y	0272	8F		.BYTE \$8F ;E
0241	9D 68 02		STA \$0268,X	0273	A7		.BYTE \$A7 ;B
0244	C8		INY	0274	40		.BYTE \$40 ;.
0245	E8		INX	0275	3D		.BYTE \$3D ;M
0246	E0 12		CPX #\$12	0276	8F		.BYTE \$8F ;E
0248	D0 F4		BNE \$023E	0277	00		.BYTE \$00 ;sp
024A	4C 00 02		JMP \$0200	0278	00		.BYTE \$00 ;sp
024D	A2 01	DELA1	LDX #\$01	0279	00		.BYTE \$00 ;sp
024F	A0 15		LDY #\$15	027A	00	DECA	.BYTE \$00 ; decale
0251	CA	DL1	DEX	027B	FF	NEXT	.BYTE \$FF

TITLE Défilement bannière
TITREPAGE 2 OF 2
PAGE DE

Dump HEX :

```
0200: AE 61 02 BD 62 02 8D 02 80 AE 61 02 BD 68 02 8D
0210: 03 80 20 4D 02 EE 61 02 AE 61 02 E0 06 D0 E1 A2
0220: 00 8E 61 02 CE 7B 02 AD 7B 02 C9 00 D0 D2 A9 FF
0230: 8D 7B 02 A0 00 A2 00 B9 68 02 8D 7A 02 C8 B9 68
0240: 02 9D 68 02 C8 E8 E0 12 D0 F4 4C 00 02 A2 01 A0
0250: 15 CA E0 00 D0 FB 88 A9 00 8D 03 80 C0 00 D0 F6
0260: 60 00 9F AF B7 BB BD BE 8D 85 BD 23 8F AE 40 1F
0270: 37 A9 8F A7 40 3D 8F 00 00 00 00 FF
```

Format Intel HEX :

```
:10020000AE6102BD62028D0280AE6102BD68028DE8
:100210000380204D02EE6102AE6102E006D0E1A251
:10022000008E6102CE7B02AD7B02C900D0D2A9FF55
:100230008D7B02A000A200B968028D7A02C8B9685D
:10024000029D6802C8E8E012D0F44C0002A201A0AE
:1002500015CAE000D0FB88A9008D0380C000D0F64D
:1002600060009FAFB7BBBD8E8D85BD238FAE401F65
:0C02700037A98FA7403D8F00000000FF61
:00000001FF
```