



PX41CX interface



HP41 source program
BINDEC.txt

001	LBL 'DECBIN' ; Key: 14	C0 00 F7 31 44 45 43 42 49 4E
002	CLST	73
003	10	11 10
004	STO 01	31
005	2	12
006	STO 02	32
007	10	11 10
008	/	43
009	+	40
010	FIX 1	9C 01
011	STOP	84
012	LBL 'BINDEC' ; Key: 15	C0 00 F7 41 42 49 4E 44 45 43
013	2	12
014	STO 01	31
015	10	11 10
016	STO 02	32
017	CLST	73
018	2.1	12 1A 11
019	FIX 2	9C 02
020	STOP	84
021	LBL 'CONV' ; Key: 11	C0 00 F5 01 43 4F 4E 56
022	FIX 0	9C 00
023	STO 00	30
024	STO 03	33
025	STO 04	34
026	RCL 01	21
027	RCL 02	22
028	-	41
029	STO 05	35
030	LBL 01	02
031	RCL 04	24
032	RCL 02	22
033	/	43
034	INT	68
035	STO 04	34
036	X=0?	67
037	GTO 02	B3 00
038	RCL 05	25
039	*	42
040	ST+ 00	92 00
041	RCL 01	21
042	ST* 05	94 05
043	GTO 01	B2 00
044	LBL 02	03
045	CLX	77
046	STO T	91 70
047	STO Z	91 71
048	STO Y	91 72
049	RCL 03	23
050	RCL 00	20
051	STOP	84
052	END	C0 00 0D



PX41CX interface



Program : BINDEC

Row 1 (Lines 1-3)



Row 2 (Lines 3-12)



Row 3 (Lines 12-17)



Row 4 (Lines 18-21)



Row 5 (Lines 21-32)



Row 6 (Lines 33-42)



Row 7 (Lines 43-51)



Row 8 (Lines 52-52)



End of Bar Code - Total of 8 Rows