



PX41CX interface



HP41 source program
MASTERMIND.txt

001	LBL 'MM' ; Key: 34	C0 00 F3 33 4D 4D
002	FIX 00	9C 00
003	CF 29	A9 1D
004	15	11 15
005	PSIZE	A6 5E
006	RCL 06	26
007	X=0?	67
008	TIME	A6 9C
009	PI	72
010	+	40
011	FRC	69
012	STO 06	36
013	LBL 01	02
014	'NB COL=?'	F8 4E 42 20 43 4F 4C 3D 3F
015	PROMPT	8E
016	1	11
017	-	41
018	1 E3	11 1B 13
019	/	43
020	STO 07	37
021	STO 09	39
022	'NB LET=?'	F8 4E 42 20 4C 45 54 3D 3F
023	PROMPT	8E
024	STO 08	38
025	'UN INSTANT'	FA 55 4E 20 49 4E 53 54 41 4E 54
026	AVIEW	7E
027	TONE 03	9F 03
028	CLA	87
029	LBL 02	03
030	XEQ 08	E0 00 08
031	STO IND 09	91 89
032	POSA	A6 5C
033	-1	1C 11
034	X#Y?	79
035	GTO 02	B3 00
036	RCL IND 09	90 89
037	XTOA	A6 6F
038	ISG 09	96 09
039	GTO 02	B3 00
040	ASTO 14	9A 0E
041	0	10
042	STO 12	3C
043	'A VOUS ...'	FA 41 20 56 4F 55 53 20 2E 2E 2E
044	LBL 07	08
045	AON	8C
046	TONE 04	9F 04
047	PROMPT	8E
048	ASTO 13	9A 0D
049	1	11
050	ST+ 12	92 0C
051	RCL 13	2D
052	RCL 14	2E
053	X=Y?	78

054	GTO 03	B4 00
055	AVIEW	7E
056	RCL 07	27
057	STO 09	39
058	0	10
059	STO 10	3A
060	STO 11	3B
061	CLA	87
062	ARCL 13	9B 0D
063	LBL 04	05
064	RCL IND 09	90 89
065	POSA	A6 5C
066	STO 08	38
067	-1	1C 11
068	X=Y?	78
069	GTO 06	B7 00
070	RCL 08	28
071	RCL 09	29
072	INT	68
073	X=Y?	78
074	GTO 05	B6 00
075	1	11
076	ST+ 11	92 0B
077	GTO 06	B7 00
078	LBL 05	06
079	1	11
080	ST+ 10	92 0A
081	LBL 06	07
082	ISG 09	96 09
083	GTO 04	B5 00
084	>'	F2 7F 20
085	ARCL 10	9B 0A
086	>'-'	F2 7F 2D
087	ARCL 11	9B 0B
088	>'	F2 7F 20
089	ARCL 12	9B 0C
090	GTO 07	B8 00
091	LBL 03	04
092	'GAGNE EN '	F9 47 41 47 4E 45 20 45 4E 20
093	ARCL 12	9B 0C
094	>' COUPS.'	F8 7F 20 43 4F 55 50 53 2E
095	AOFF	8B
096	BEEP	86
097	PROMPT	8E
098	GTO 01	B2 00
099	LBL 08	09
100	RCL 06	26
101	X=0?	67
102	TIME	A6 9C
103	9821	19 18 12 11
104	*	42
105	0.211327	10 1A 12 11 11 13 12 17
106	+	40
107	FRC	69
108	STO 06	36
109	RCL 08	28
110	*	42
111	65	16 15
112	+	40
113	INT	68
114	RTN	85
115	END	C0 00 0D



PX41CX interface



Program : MASTERMIND

Row 1 (Lines 1-5)



Row 2 (Lines 5-14)



Row 3 (Lines 14-19)



Row 4 (Lines 20-24)



Row 5 (Lines 25-27)



Row 6 (Lines 27-34)



Row 7 (Lines 35-41)



Row 8 (Lines 41-44)



Row 9 (Lines 45-54)



Row 10 (Lines 54-64)



Row 11 (Lines 65-74)



Row 12 (Lines 74-82)



Row 13 (Lines 83-88)



Row 14 (Lines 88-92)



Row 15 (Lines 92-94)



Row 16 (Lines 94-103)



Row 17 (Lines 103-106)



Row 18 (Lines 107-115)



End of Bar Code - Total of 18 Rows