

TITLE **LEDS : affichage alterné**
TITRE

PAGE **1** OF **1**
PAGE DE

Affichage des LEDs alterné :

●●●●●●●● puis ○●●●●●●●

Exécuter le programme : [ADDR] 0200 [GO]

```

0200                                * = $0200
0200 A9 AA      ALTERN LDA #$AA
0202 8D 00 80    STA $8000
0205 20 13 02    JSR $0213
0208 A9 55      LDA #$55
020A 8D 00 80    STA $8000
020D 20 13 02    JSR $0213
0210 4C 00 02    JMP $0200
0213 A2 FF      DELAI LDX #$FF
0215 A0 FF      LDY #$FF
0217 CA        DL1   DEX
0218 88        DL2   DEY
0219 C0 00      CPY #$00
021B D0 FB      BNE $0218
021D E0 00      CPX #$00
021F D0 F6      BNE $0217
0221 60        RTS

```

```

0200: A9 AA 8D 00 80 20 13 02 A9 55 8D 00 80 20 13 02
0210: 4C 00 02 A2 FF A0 FF CA 88 C0 00 D0 FB E0 00 D0
0220: F6 60

```

```

:10020000A9AA8D0080201302A9558D008020130219
:100210004C0002A2FFA0FFCA88C000D0FBE000D0C3
:02022000F66086
:00000001FF

```